

C-06D Ith:16A Tj:9A	C-09D Ith:20A Tj:9A	C-11D Ith:25A Tj:12A	C-12D Ith:25A Tj:16A	C-18D Ith:32A Tj:22A	C-25D Ith:40A Tj:32A	C-35D Ith:50A Tj:42A	C-45D Ith:60A Tj:55A	C-55D Ith:60A Tj:65A	C-65D Ith:80A Tj:80A	C-85D Ith:125A Tj:105A	C-100D Ith:130A Tj:110A
---------------------------	---------------------------	----------------------------	----------------------------	----------------------------	----------------------------	----------------------------	----------------------------	----------------------------	----------------------------	------------------------------	-------------------------------

C-12D10G7

1 2 3 4

1. Series	C						
2. Model Name	06D, 09D, 11D, 12D, 18D, 25D, 35D, 45D, 55D, 65D, 80D, 100D						
3. Aux. Contact	10:1a	01:1b	11:1a1b		22:2a2b		
4. Coil Voltage (5 : 50Hz · 6 : 60Hz · 7 : 50/60Hz · D : DC)	12V:Y 24V:A 42V:B 48V:C	100V:W 110V:D 115V:T 120V:E	190V:F 200V:R 208V:U 220V:G	227V:X 230V:H 240V:I 380V:J	400V:K 415V:L 440V:M 460V:S	480V:N 525V:O 550V:V 575V:P	600V:Q

Stycznik 4-biegunowy (4-biegunowy)

Oznaczenie modelu

C-12D22G7

1 2 3



1. Model

09D	11D	12D	25D
-----	-----	-----	-----

2. Contacts

09D	11D	12D	25D
40	4a	40	4a
22	2a2b	22	2a2b
04	4b	04	4b

3. Coil Voltage

See Coil Voltage Table



C-12D22



C-25D22

Model Name	Contact N/O N/C	Insulation Voltage	AC1 duty at 40°C	AC3 Ie	Weight Kg
C-09D40	4 -	1000V	20A	9A	0.326
C-09D22	2 2	1000V	20A	9A	0.326
C-09D04	- 4	1000V	20A	9A	0.326
C-11D40	4 -	1000V	25A	12A	0.326
C-11D22	2 2	1000V	25A	12A	0.326
C-11D04	- 4	1000V	25A	12A	0.326
C-12D40	4 -	1000V	25A	16A	0.326
C-12D22	2 2	1000V	25A	16A	0.326
C-12D04	- 4	1000V	25A	16A	0.326
C-25D40	4 -	1000V	40A	32A	0.525
C-25D22	2 2	1000V	40A	32A	0.525
C-25D04	- 4	1000V	40A	32A	0.525